QUEST SEMI | TECHNICAL APPLICATION DOCUMENT

Document ID: AN-2026-04 | Target Variants: 5kV / 10kV SiC MOSFET Platform

---

Optimizing Thermal Management & Power Density in Bidirectional BESS Converters Using Ultra-High-Voltage SiC MOSFETs

1. Abstract

Modern utility-scale Battery Energy Storage Systems (BESS) demand unprecedented power densities and bidirectional efficiencies exceeding 98.5%. Traditional silicon-based insulated-gate bipolar transistors (IGBTs) are constrained by low switching frequencies (less than 5 kHz) and substantial switching losses, necessitating massive liquid-cooling infrastructures. This application note explores thermal optimization methodologies when replacing legacy silicon with **Quest Semi 5kV and 10kV Silicon Carbide (SiC) MOSFETs** in bidirectional multi-megawatt central inverters. By leveraging the ultra-low switching losses and superior thermal conductivity of wide-bandgap (WBG) technology, engineers can increase switching frequencies up to 25 kHz, downsize magnetic filters by 60%, and reduce total cooling system overhead by up to 75%.

2. The High-Voltage BESS Thermal Challenge

Scaling modern battery banks up to higher DC bus topologies (1500V to 3000V DC) drastically cuts current conduction losses (I^2R) across the DC bus. However, at these elevated voltages, traditional Silicon IGBTs encounter severe performance bottlenecks. These include prolonged tail currents during turn-off that generate massive switching energy losses, thermal runaway risks due to internal resistance spiking with temperature, and heavy heatsink volumetrics. Managing the resulting thermal dissipation requires massive air-cooled configurations or complex liquid-to-water heat exchangers, severely limiting system power density (kW/m^3). Quest Semi's high-voltage SiC MOSFETs resolve these bottlenecks by offering a breakdown strength 10x higher than silicon and near-zero reverse recovery charge.

3. Thermal Evaluation: Quest Semi SiC vs. Legacy Silicon

The performance data below outlines a 1.5 Megawatt (MW) bidirectional three-phase ANPC inverter configuration operating at a 1500V DC bus link.

Thermal & Operational Metric	Legacy Silicon IGBT (3.3kV)	Quest Semi SiC MOSFET (5kV)	Performance Variant
Max Switching Frequency (f_{sw})	3.5 kHz	20 kHz	5.7x Frequency Boost
Total Inverter Efficiency (Peak)	96.8%	99.1%	2.3% Loss Reduction
Junction-to-Case Thermal Res. (R_{thJC})	0.045 °C/W	0.018 °C/W	60% Faster Heat Dissipation
Required Heatsink Volume (cm^3)	14,200 cm^3	4,100 cm^3	71% Size Reduction

Cooling Architecture Requirement	Active Liquid Chillers	Forced Air / Simple Loop	Eliminates Chiller Overhead

4. Critical Implementation Guidelines

4.1. Minimizing Loop Inductance to Stabilize Junction Temperature

Because Quest Semi's ultra-high-voltage MOSFETs switch massive currents within nanoseconds, high di/dt rates can interact with stray circuit inductance, triggering transient voltage overshoots. Designers must keep loop stray inductance strictly under 15 nH by utilizing laminated bus bars and placing high-frequency ceramic snubber capacitors as close to the terminal pins as possible.

4.2. Thermal Interface Material (TIM) Selection

Silicon Carbide's smaller die footprint concentrates thermal loads over a reduced physical plane. Achieving peak efficiency requires phase-change TIMs or high-performance pastes with a bulk thermal conductivity ≥ 6.0 W/m·K coupled with precise mounting torques to clear residual air gaps.

4.3. Gate Driver Protection Against High dv/dt Noise

Aggressive switching intervals produce severe dv/dt transients exceeding 50 kV/µs. To protect control topologies from parasitic cross-conduction or latch-up risks, designers should pair components with isolated gate drivers carrying a Common Mode Transient Immunity (CMTI) rating of ≥ 150 kV/µs.

5. Conclusion

Integrating Quest Semi's 5kV and 10kV Silicon Carbide platforms into utility-scale bidirectional BESS converters directly transforms system-level economics. Lower intrinsic losses combined with faster thermal dissipation allow engineers to design around compact magnetic components, scale down liquid chiller profiles, and safely packing higher megawatt-hour limits within tighter field enclosures.

This is for informational purposes only. For medical advice or diagnosis, consult a professional. AI responses may include mistakes.